



## Split Connector Clamps (B Type)

Split connector clamps (Rod to Cable Lug Clamps) are used to connect cable lugs onto earth rods.

| Max. Rod $\Phi$<br>mm | Rod<br>Type                      | Thread<br>Size | Article<br>Number |
|-----------------------|----------------------------------|----------------|-------------------|
| 14.2                  | Threaded<br>Copperbond           | 5/8"           | RCLC 140          |
| 14.2                  | Unthreaded<br>Copperbond         |                | RCLC 141          |
| 16                    | Solid Copper/<br>Stainless Steel |                | RCLC 160          |
| 17.2                  | Threaded<br>Copperbond           | 3/4"           | RCLC 170          |
| 17.2                  | Unthreaded<br>Copperbond         |                | RCLC 171          |
| 20                    | Solid Copper/<br>Stainless Steel |                | RCLC 200          |

**Material:** Brass or Gunmetal with Stainless Steel or Brass Set Screw



Earthing

## Special Split Connector Clamps (B Type)

Split connector clamps (Rod to Cable Lug Clamps) are used to connect cable lugs onto earth rods. These clamps are designed to suit our full range of earth rods.

| Rod $\Phi$<br>mm | Bolt<br>Size | Article<br>Number |
|------------------|--------------|-------------------|
| 14.2             | M12          | SRCLC 140         |
| 17.2             | M12          | SRCLC 170         |

**Material:** Brass or Gunmetal with Stainless Steel or Brass Set Screw



## Parallel Cable Clamps

These clamps are used for connecting one or two stranded copper conductors or to the surfaces.

| Main<br>Conductor A<br>mm <sup>2</sup> | Tap<br>Conductor B<br>mm <sup>2</sup> | Article<br>Number |
|----------------------------------------|---------------------------------------|-------------------|
| 35                                     | 35                                    | PCC 35            |
| 50                                     | 50                                    | PCC 50            |
| 70                                     | 70                                    | PCC 70            |

**Material:** Copper-plated Brass

